



WIRELESS BACKHAUL

CELLULAR REPEATERS/
SIGNAL BOOSTERS

ENTERPRISE/CARRIER-CLASS
WI-FI ACCESS POINTS

SMALL CELLS

BASE STATIONS/DAS


TEST EQUIPMENT/
INSTRUMENTATION

MILITARY COMMUNICATIONS/
GPS



Making Better Networks

Ultra-LNA™

P/N	Tuning Range (GHz)	Reference Conditions	Gain (dB)	EVB NF (dB)	OP1dB (dBm)	OIP3 (dBm)	Vdd Range (V)	Idd Range (mA)	Internally Matched (50 ohms)	Package (mm)
GRF2051	0.7 - 3.8	1.9 GHz 5.0V; 70mA	19.0	0.37	21.0	36.0	2.7 - 5.0	20 - 100	No	2.0 x 2.0 QFN-12
GRF2052	1.7 - 4.5	2.5 GHz 5.0V; 70mA	19.2	0.50	21.0	38.0	2.7 - 5.0	20 - 100	No	2.0 x 2.0 QFN-12
GRF2070*	0.4 - 1.5	0.9 GHz 5.0V; 75mA	20.8	0.35	20.0	39.5	2.7 - 5.0	20 - 100	No	2.0 x 2.0 DFN-8
GRF2071*	1.4 - 2.7	1.9 GHz 5.0V; 70mA	20.0	0.35	19.0	38.5	2.7 - 5.0	20 - 100	No	2.0 x 2.0 DFN-8
GRF2072*	2.3 - 3.8	2.5 GHz 5.0V; 70mA	19.3	0.50	21.0	38.0	2.7 - 5.0	20 - 100	No	2.0 x 2.0 DFN-8
GRF2073*	3.0 - 6.0	3.6 GHz 5.0V; 70mA	18.9	0.69	18.5	36.5	2.7 - 5.0	20 - 100	No	2.0 x 2.0 DFN-8
GRF2105*	0.4 - 6.0	2.5 GHz 5.0V; 65mA	20.0	0.75	22.0	34.5	2.7 - 5.0	20 - 90	Yes	1.5 x 1.5 DFN-6
GRF2501	4.9 - 6.0	5.5 GHz 3.3V; 15mA	16.0	0.8	7.0	19.0	2.7 - 5.0	12 - 28	Yes	1.5 x 1.5 DFN-6
GRF2541 	4.9 - 6.0	5.5 GHz 3.3V; 15mA	17.5	0.9	7.0	19.0	2.7 - 5.0	12 - 28	Yes	1.5 x 1.5 DFN-6

Note: NF values for internally matched GRF2501/2541 de-embedded

PA / Power-LNA™

P/N	Tuning Range (GHz)	Reference Conditions	Gain (dB)	EVB NF (dB)	OP1dB (dBm)	OIP3 (dBm)	Vdd Range (V)	Idd Range (mA)	Internally Matched (50 ohms)	Package (mm)
GRF3610*	0.05 - 3.8	2.5 GHz 8.0V; 155mA	16.5	0.75	29.0	43.0	4.5 - 8.0	Tied to Vdd	No	SOT-89
GRF5010	0.05 - 6.0	2.5 GHz 8.0V; 130mA	17.5	0.80	28.5	44.0	4.5 - 8.0	50 - 160	No	3.0 x 3.0 QFN-16
GRF5020	0.1 - 6.0	2.5 GHz 10.0V; 170mA	17.0	0.80	30.5	44.0	4.5 - 10.0	50 - 200	No	3.0 x 3.0 QFN-16
GRF5040	0.1 - 3.8	1.9 GHz 10.0V; 220mA	18.5	0.82	31.0	46.0	4.5 - 10.0	100 - 250	No	3.0 x 3.0 QFN-16
GRF5109*	0.4 - 1.5	0.9 GHz 5.0V; 170mA	17.9	1.2	28.3	45.0	2.7 - 5.0	50 - 200	No	3.0 x 3.0 QFN-16
GRF5110*	1.5 - 2.7	1.9 GHz 5.0V; 170mA	14.8	1.3	28.8	45.0	2.7 - 5.0	50 - 200	No	3.0 x 3.0 QFN-16
GRF5115*	0.1 - 2.7	1.9 GHz 5.0V; 300mA	14.4	1.3	32.5	45.7	2.7 - 5.0	200 - 400	No	3.0 x 3.0 QFN-16
GRF5220*	0.1 - 2.7	1.9 GHz 10.0V; 200mA	18.5	1.2	33.0	44.0	4.5 - 10.0	80 - 250	No	3.0 x 3.0 QFN-16
GRF5511*	1.5 - 6.0	5.5 GHz 8.0V; 160 mA	16.0	2.6	29.5	48.0	4.5 - 10.0	50 - 200	No	3.0 x 3.0 QFN-16
GRF5512*	2.5 - 6.0	5.5 GHz 5.0V; 75mA	15.4	1.5	26.8	38.0	2.7 - 6.0	50 - 125	No	3.0 x 3.0 QFN-16




GUERRILLA BLOC™ TECHNOLOGY

Fully integrated ultra-low noise amplifier, driver and PA modules

High Linearity Gain Blocks to C/X Band

P/N	Tuning Range (GHz)	Reference Conditions	Gain (dB)	EVB NF (dB)	OP1dB (dBm)	OIP3 (dBm)	Vdd Range (V)	Idd Range (mA)	Internally Matched (50 ohms)	Package (mm)
GRF3012*	0.05 - 3.8	0.9 GHz 5.0V; 85mA	15.2	1.9	22.0	39.0	3.0 - 9.0	Tied to Vdd	Yes	SOT-89
GRF3013*	0.05 - 5.0	1.9 GHz 8.0V; 140mA	17.2	2.0	27.0	42.0	3.0 - 9.0	Tied to Vdd	Yes	SOT-89
GRF3014*	0.05 - 3.8	0.9 GHz 8.0V; 190mA	15.4	3.3	27.4	41.5	3.0 - 9.0	Tied to Vdd	Yes	SOT-89
GRF3015*	0.05 - 5.0	1.9 GHz 5.0V; 85mA	17.9	1.2	22.7	39.0	3.0 - 9.0	Tied to Vdd	Yes	SOT-89
GRF2012*	0.05 - 5.0	0.9 GHz 5.0V; 90mA	15.2	1.9	22.7	40.0	3.0 - 9.0	30 - 120	Yes	1.5 x 1.5 DFN-6
GRF2013*	0.05 - 8.0	1.9 GHz 5.0V; 90mA	18.8	1.4	23.5	40.0	3.0 - 9.0	40 - 120	Yes	1.5 x 1.5 DFN-6
GRF2014*	0.05 - 3.8	0.9 GHz 8.0V; 165mA	15.9	3.3	28.0	42.8	3.0 - 9.0	50 - 180	Yes	1.5 x 1.5 DFN-6
GRF2003	0.05 - 11.0	6.0 GHz 5.0V; 55mA	12.0	3.8	14.5	28.0	3.0 - 5.0	40 - 80	Yes	1.5 x 1.5 DFN-6
GRF2004	0.05 - 10.0	8.0 GHz 5.0V; 100mA	12.0	1.7	13.0	28.0	3.0 - 5.0	60 - 120	Yes	1.5 x 1.5 DFN-6
GRF3042	Near DC - 13.0	8.0 GHz 45mA	12.5	2.2	14.5	24.5	>= 7.0	35 - 60	Yes	1.5 x 1.5 DFN-6
GRF3044	Near DC - 11.0	8.0 GHz 100mA	12.7	1.8	16.5	27.0	>= 7.0	60 - 120	Yes	1.5 x 1.5 DFN-6

Broadband LNA / Linear Drivers

P/N	Tuning Range (GHz)	Reference Conditions	Gain (dB)	EVB NF (dB)	OP1dB (dBm)	OIP3 (dBm)	Vdd Range (V)	Idd Range (mA)	Internally Matched (50 ohms)	Package (mm)
GRF2505	1.7 - 6.0	5.5 GHz 5.0V; 40mA	13.0	1.0	20.5	35.0	1.8 - 5.0	20 - 60	Yes	1.5 x 1.5 DFN-6
GRF2710	8.0 - 13.0	11.0 GHz 5.0V; 40mA	14.0	2.1	13.0	21.0	4.5 - 8.0	15 - 35	Yes	1.5 x 1.5 DFN-6
GRF3502*	0.1 - 3.8	2.5 GHz 5.0V; 70mA	14.0	0.85	23.5	36.0	3.0 - 5.0	Tied to Vdd	Yes	SOT-89
GRF3503*	0.1 - 2.7	1.9 GHz 5.0V; 100mA	14.0	0.75	25.0	40.5	3.0 - 5.0	Tied to Vdd	Yes	SOT-89
GRF3505*	0.1 - 2.7	1.9 GHz 5.0V; 160mA	15.0	0.75	27.5	41.0	3.0 - 5.0	Tied to Vdd	No	SOT-89
GRF4002	0.1 - 3.8	2.5 GHz 5.0V; 70mA	15.0	0.85	23.5	36.5	1.8 - 5.0	20 - 80	Yes	1.5 x 1.5 DFN-6
GRF4003	0.1 - 3.8	2.5 GHz 5.0V; 95mA	12.5	0.85	25.0	41.0	1.8 - 5.0	30 - 120	Yes	1.5 x 1.5 DFN-6
GRF4004	0.1 - 3.8	2.5 GHz 5.0V; 135mA	12.5	0.85	26.5	43.0	1.8 - 5.0	30 - 150	No	1.5 x 1.5 DFN-6
GRF4005	0.1 - 3.8	2.5 GHz 5.0V; 170mA	13.0	0.85	27.5	43.0	1.8 - 5.0	50 - 200	No	1.5 x 1.5 DFN-6
GRF4042 	0.4 - 2.7	1.9 GHz 5.0V; 70mA	15.5	1.0	22.0	36.0	1.8 - 5.0	20 - 80	Yes	2.0 x 2.0 QFN-12



Guerrilla Armor™ / Bypass Mode

* Samples / EVB available Q3 2016



Making Better Networks

Guerrilla RF's high performance RF and Microwave IC products enable greater coverage areas and higher data rates for wireless networks. Focused on a wide variety of infrastructure and general market applications, our unique products utilize our patented Guerrilla Armor technology, world class IC design talents, and cutting edge device technologies to deliver best in class performance. Our team of industry veterans are committed to providing detailed, custom applications support through all stages of your product design process from initial prototyping through mass production. Please see the Guerrilla RF website for all the latest product information at:
www.guerrilla-rf.com

CONTACT US



1196 Pleasant Ridge Road
Suite 5
Greensboro, NC 27409



336.510.7840



sales@guerrilla-rf.com



www.guerrilla-rf.com

This document, including the information contained in it, is provided by Guerrilla RF as a service to its customers and may be used for informational purposes only by the customer. Guerrilla RF assumes no responsibility for errors or omissions in this document or the information contained herein. Information provided is believed to be accurate and reliable, however, no responsibility is assumed by Guerrilla RF for its use, nor for any infringement of patents, or other rights of third parties, resulting from its use. Guerrilla RF assumes no liability for any product information, or other information provided hereunder, including the sale, distribution, reproduction or use of Guerrilla RF products, information or materials.

No license, whether express, implied, by estoppel, by implication or otherwise is granted by this document for any intellectual property of Guerrilla RF, or any third party, including without limitation, patents, patent rights, copyrights, trademarks and trade secrets. All rights are reserved by Guerrilla RF.

All information herein, products, product information, datasheets, and datasheet information are subject to change and availability without notice. Guerrilla RF reserves the right to change component circuitry, recommended application circuitry and specifications at any time without prior notice. Guerrilla RF may further change its datasheet, product information, documentation, products, services, specifications or product descriptions at any time, without notice. Guerrilla RF makes no commitment to update any materials or information and shall have no responsibility whatsoever for conflicts, incompatibilities, or other difficulties arising from any future changes.

GUERRILLARF INFORMATION, PRODUCTS, PRODUCT INFORMATION, DATASHEETS AND DATASHEET INFORMATION ARE PROVIDED "AS IS" AND WITHOUT WARRANTY OF ANY KIND, WHETHER EXPRESS, IMPLIED, STATUTORY, OR OTHERWISE, INCLUDING FITNESS FOR A PARTICULAR PURPOSE OR USE, MERCHANTABILITY, PERFORMANCE, QUALITY OR NON-INFRINGEMENT OF ANY INTELLECTUAL PROPERTY RIGHT; ALL SUCH WARRANTIES ARE HEREBY EXPRESSLY DISCLAIMED. GUERRILLA RF DOES NOT WARRANT THE ACCURACY OR COMPLETENESS OF THE INFORMATION, TEXT, GRAPHICS OR OTHER ITEMS CONTAINED WITHIN THESE MATERIALS. GUERRILLA RF SHALL NOT BE LIABLE FOR ANY DAMAGES, INCLUDING BUT NOT LIMITED TO ANY SPECIAL, INDIRECT, INCIDENTAL, STATUTORY, OR CONSEQUENTIAL DAMAGES, INCLUDING WITHOUT LIMITATION, LOST REVENUES OR LOST PROFITS THAT MAY RESULT FROM THE USE OF THE MATERIALS OR INFORMATION, WHETHER OR NOT THE RECIPIENT OF MATERIALS HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

Customers are solely responsible for their use of Guerrilla RF products in the Customer's products and applications or in ways which deviate from Guerrilla RF's published specifications, either intentionally or as a result of design defects, errors, or operation of products outside of published parameters or design specifications. Customers should include design and operating safeguards to minimize these and other risks. Guerrilla RF assumes no liability or responsibility for applications assistance, customer product design, or damage to any equipment resulting from the use of Guerrilla RF products outside of stated published specifications or parameters.